

FAULTY OPERATION AND ITS POSSIBLE DIAGNOSIS

LED indicator does not light up

AC power failure.

LED indicator is red, luminaire doesn't light up

The battery is disconnected or damaged.

The luminaire does not operate in emergency mode the required time for a selected model

It is possible that the battery requires a full charge cycle (24h). If after 24 hours of charging the luminaire still does not keep a predefined autonomy, it is possible that the battery is run-down or damaged, e.g. due to possible incorrect formatting and needs to be replaced.

RECOMMENDED PERIODICAL MAINTENANCE

The luminaire should be tested on regular basis in accordance with valid laws and regulations. The results of the tests should be recorded and stored for the use of a fire safety inspector.

One time daily

It is suggested to check visually if the LED indicator in the luminaire lights up in green.

One time each month

It is necessary to perform a function test by disconnecting the AC power supply and checking whether the luminaire is operating in emergency mode - the green LED indicator should turn off, and LED light source light up. For MT version the test should be initiated manually.

One time each year

In order to make an autonomy test, disconnect the AC power supply and test if the luminaire operates in emergency mode for a specified time. If the autonomy time of emergency operation is not sufficient, the battery needs to be fully recharged and the test is to be carried out again. If the result of the test continues to be negative, the battery needs to be replaced. For MT version the test should be initiated manually.

CAUTION!


All damage that might occur as an effect of the device being used not in accordance to this instruction will result in loss of guarantee.

Used or damaged lamps including batteries, are subject to be recycled. They should be delivered to the point of collection of electrical and battery waste or to the manufacturer.



The light source contained in this luminaire shall only be replaced by the manufacturer or his service agent or a similar qualified person.

Handling of obsolete equipment



Pursuant to the Act of 29 July 2005 on waste electrical and electronic equipment and the Act of 24 April 2009 on batteries and accumulators, the presented device, after use, due to hazardous substances contained in it, is subject to collection of waste electrical and electronic equipment. Detailed information on WEEE collection can be obtained from municipal authorities.

intelight
Intelight Sp. z o.o.
19, Gwiaździsta str.
01-651 Warsaw, Poland

intelight

STARLET EXTERNAL LED EMERGENCY LUMINAIRE

Installation and maintenance instructions



STARLET EXTERNAL SO



STARLET EXTERNAL SC

Versions:

STARLET EXTERNAL SO

STARLET EXTERNAL SC

TECHNICAL SPECIFICATIONS:

Light source (non-replaceable):	White LED 3W
Operating modes:	A (NM) – emergency operation
Test versions:	MT – manual test
Emergency autonomy*:	1h, 2h or 3h
Battery* (non-replaceable):	NiCd 3,6V 1300 ÷ 2500mAh or NiMH 3,6V 2000mAh ÷ 4200mAh
Battery charging duration:	24h
Power supply*:	MT: 220-240V AC 50Hz; CB: 220V AC/DC
Max. power:	4W
Module:	Starlet External
Luminous flux:	120-200lm
Enclosure IP rating:	IP41
Ambient temperature:	10°C ÷ 40°C

*- depending on model



INTRODUCTION

1. The lamp should be installed when power supply is off. Safety rules, construction and electrical installation standards should be followed all the time.
2. The luminaire should not be powered with circuits connected to inductive power-receiving devices at the same time. This type of solution may cause damage to the electronic module of the luminaire.
3. The luminaire should be used indoors.

INSTALLATION

1. Before installation one has to make sure that the luminaire will be connected to 220-240VAC power supply by the use of minimum a 1,5mm² wire.
2. In order to install the luminaire on a ceiling, first one need to open the luminaire housing by pressing with a screwdriver on one of the latches on the side of the housing, which fix the luminaire cover to its base. After releasing all the three latches and decomposing the housing, one need to fix the luminaires' base containing electronics and a battery pack to the ceiling using two mounting holes designed for this purpose. A large hole with a grommet is designed to conduct the power cables, one need to cut a right size hole in the grommet to ensure proper sealing.

3. Prepare power cable and connect all the wires to the appropriate terminal block entries.
4. The description of luminaire terminals:
L - phase wire - brown or black insulation colour; power source for battery charging, presence signaled by signal LED lighting up in green
N - neutral wire - blue insulation colour
PE - earth wire - yellow and green insulation colour
5. **EMERGENCY OPERATION (A, NM).** To enable emergency operation of the luminaire, the AC mains power has to be connected to appropriate terminals: **L** (phase) and **N** (neutral). One need always to remember about connecting protection earth (**PE**) wire. The luminaire should be constantly supplied by power - voltage drop on L will result in emergency mode activation.
6. Before connecting the luminaire to the mains network, insert the white battery plug into the socket on the PCB.
7. Please remember to indicate the date of installation on the label attached to the battery pack.
8. In order to finish the installation, one need to click the luminaire's body in to the mounting base.
9. For quick operation testing – switch on the AC power supply. The green LED indicator should light up, signaling the mains connection and battery charging. After battery is charged, the LED indicator should still light up in green, what means readiness for emergency operation. By pressing the test button, one can check if the luminaire enters the emergency operation when the power supply is off. The way how to press the test button and how to read the luminaire's behaviour depends on its version. You can find detailed information in the "TESTING" section.
10. First-time charge of the luminaire battery pack should be carried out continuously for 48 hours. This will allow appropriate formatting of the battery pack. During the first-time charge, no testing should be carried out and power supply should not be disconnected for any other purpose. Power supply should be disconnected after 48 hours for the first time. The luminaire should complete a full emergency operation cycle, after which it should be connected to power supply for another 36 hours. This sequence shall complete the formatting cycle.

OPERATION

Emergency operation mode

In this mode (A, NM) the luminaire does not light when powered by AC supply voltage. Correct operation of the device is confirmed by LED indicator lighting up in green. The battery is being continuously trickle charged for the purpose of a possible emergency operation. When AC power supply is off (no voltage on L), the luminaire automatically starts operating in emergency mode and the source of light is activated for the period specific for a particular model. During emergency operation, the LED indicator is off.

Information on lamp operation

The luminaire operates correctly and charging circuit works if the LED indicator lights up in green. If the indicator does not light up, the lamp is not operating with AC power supply on or any luminaire's element has been damaged. See more info about signaling in "TESTING" section.

Battery pack

The luminaire is equipped with a rechargeable Ni-Cd or Ni-MH battery pack. Please remember to carry out the correct first-time charge cycle. A proper formatting process (see "INSTALLATION", p.10) enables to achieve a sufficient battery's capacity and reaching its nominal autonomy during future emergency operation. It is suggested to discharge and then to re-charge the battery every three months, even if it hasn't been used, in order to extend its performance. It is recommended to replace the battery once every four years of operation or in a case of poor test results. Obsolete batteries, similarly to packaging, fluorescent lamps or electronics, are recyclable products that should be disposed to a recyclable waste collection point.

TESTING

STARLET EXTERNAL LED luminaire can be delivered in manual MT test version. It is equipped with a TEST button, which can be used for optional manual initiation of tests. It enables to test emergency operation of the luminaire at any time.

MT manual test version

When the emergency luminaire is connected to mains and there is no voltage drop, pressing and holding TEST button will result in activation of the "voltage drop" mode, the signal LED will go off and the luminaire should light up. When the button is released - the luminaire will switch back into its standard operation mode.

The above action means that in a case of emergency mode version the luminaire will go from unlit to illuminated. In a case of mains and emergency mode the luminaire will change a power source, from mains to a battery supply, the switch-over moment should be visible as a quick blink – during a very short while the light source will be off.

CB central battery version

Note – CB version can be equipped in a test button, however it is in this case inactive. The button pressing will not cause any luminaire's reaction.

CB version is being monitored directly by a central battery system controller, in a way depending on such system's possibilities and settings.